MS/Standard
special insert arrangements

Insert Arrangement	Service Rating	Total Contacts	Contact Size										
			4/0	2/0	0	4	8	12	16	Coax**			
										0	4	8	12
14S-A7	A	7							7				
16-59	A	4						4					
20-26	A	19							19				
20-51	A	3					3						
20-57	A	7						7*					
20-58	A	10						5	5				
20-59	A	3					3*						
20-66	A	6						5*	1				
20-79	A/D	8						1	7				
22-63	A	12						4	8				
22-65	A/D	8						8*					
22-70	A	13						8	5				
22-80	A	3					3*						
24-19	A	12							12				
24-51	A	5					5						
24-52	Hi Volt.	1						1					
24-53	A	5					5						
24-58	A	13					3	3	7				
24-59	A	14						7	7				
24-60	A	7					7*						
24-65	A	15						11	4				
24-66	D	7						7					
24-67	Inst.	19						19					
24-71	A	7					7*						
24-75	A	7					7*						
24-79	A	5					5						
24-80	Inst.	23							23				
24-84	A	19						1					18
24-96	Inst.	28							28				
24-AJ	A	25							25				
28-51	A	12						12					
28-59	A	17						7	10				
28-66	A	16					2	14					
28-72	Coax	3									3		
28-74	A	16					7*		9				
28-75	A	16					7*		9				
28-79	A	16					7		9				
28-82	D	6					2	4					
28-84	A	9					9						
28-AY	A	9				4			5				
32-14	D	13						13					
32-25	A	25						25					
32-31	A	31							31				
32-48	Inst.	48							48				
32-52	D	8			2			6					
32-53	Inst./E	42						5	37				
32-56	A	30						6*	24				
32-57	Coax	8						6		2			
32-58	Coax	4									4		
32-59	A	42							40			2	
32-60	A	23							15			8	
32-62	Coax	23				2	1	2	16			2	
32-64	Inst.	54							54				
32-68	A	16							12		4		
32-73	A	46							46				
32-75	Coax	9						2				7	
32-76	A	19						19					
32-79	D	5				4	1						
32-82	A	16				4			12				

Insert Arrangement	Service Rating	Total Contacts	Contact Size										
			4/0	2/0	0	4	8	12	16	Coax**			
										0	4	8	12
32-AF	A	55							55				
36-22	D	22						22					
36-51	D	4			2	2							
36-54	A	39					8		31				
36-55	A	39					8*		31				
36-59	A	53						3*	50				
36-60	A	47						7*	40				
36-64	Coax	4								4			
36-65	Coax	4								4			
36-71	A	53						3	50				
36-73	Coax	7									7		
36-74	A	44							43			1	
36-75	A	48							48*				
36-76	A	47							47				
36-77	D	7				7							
36-78	A	14					12		2				
36-79	A	20						20					
36-80	A	20						20*					
36-83	Coax	7									7		
36-85	A/D	35							35*				
36-97	C	1	1										
36-99	D	12				3	3	3	3				
36-AF	A	48							48				
40-5	A	5			5								
40-10	A	29				4	9		16				
40-30	A	30				1		29					
40-35	D	35						35					
40-53	A	60							60				
40-57	E	4			4								
40-61	A	59					1	3	55				
40-62	A	60							60				
40-63	A	61							61*				
40-64	Coax	36						3	20			13	
40-66	Coax	4								4			
40-67	A	11							1		10		
40-68	A	21					21						
40-70	A	61							61				
40-72	A	11							1		10		
40-73	A	61							61				
40-74	A	6						1		4	1		
40-75	E	5			4			1					
40-80	A	11				10			1				
40-81	A	62							62*				
40-82	A	62							62				
40-85	A	60							60*				
40-86	E	4								4			
40-87	D	7				7							
40-AD	A	8			4		4						
40-AG	A	38						38					
40-AP	E	2	2										
40-AR	Inst.	13			3	3		7					
40-AS	A	40						25	15				
40-AT	A	43					1	24	18				
40-AU	A	14				3	10		1				
40-AV	D	3		3									
44-52	A	104							104				
44-53	A	36							18			18	
48-51	A	56					10		42	4			
48-52	A	61							56	5			
48-53	D	37						37					
48-54	A	56					10		42	4			
48-55	A	78				6	2	2	68				
48-57	A	56			4		10		42				

* Crimp contacts accommodate wire the same size as the contact as well as wire of the next smaller, even size. Arrangements identified with an asterisk (*) are exceptions. See insert arrangement drawings on pages 38-48 for application wire size.

** Coaxial cable data can be found on insert arrangement drawings, pages 38-48. For further information on coaxial contacts and cable see catalog 13-139.